


Open Flash tool, FlashTool_v5. FlashTool_v5.1424.00 →Flash_tool.exe


Click Scatter/Config File, choose

E:\LinkIt-ONE-IDE\hardware\tools\mtk\firmware\LinkIt_ONE\1.0.48


It's s a .cfg file.




Option to choose USB Download/Read and USB Download without battery, as shown below:




Option -> FormatFat:




Choose Format FAT




The direction of switch should like this:



Click Download, and then connect your LinkIt ONE to PC,



And now, it start to update the firmware.



Finally, it's done.

